

# FEB2 Slow Control Requirements and Constraints

Ver. 1.0, July 30, 2024

The FEB2 slow control, including board initialization and monitoring, is implemented through a series of IC and EC transactions that write or read IpGBT control and data IpGBT registers. The IC and EC channels are embedded in the downlink data stream to the two onboard control IpGBTs. Control IpGBT registers are written or read directly through IC transactions as defined in table 3.3 of the IpGBTv1 manual. EC transactions are passed on from the control IpGBTs to data IpGBTs using an onboard EC bus and can write or read data IpGBT registers.

In terms of board initialization, there are several onboard components that need configuration including the COLUTAv4 ADCs, ALFE2 PA/S, VTRx+ and the IpGBTs. The IpGBTs are configured via their slow control register interface. The remaining board components are configured via the IpGBT I2C buses, which are controlled through IpGBT slow control registers. Additionally, there are two slow control modes that can be used, the default mode which relies on both control IpGBT optical links working and a redundant mode where only one optical link is available.

Each type of onboard component has a specific configuration scheme. However, the implementation of the IpGBT I2C interface means that a similar set of IC and EC transactions are required in all cases. These transactions would ideally be implemented in firmware controlling the slow control interface to the FEBs.

## 1. Required IC and EC transactions for slow control

The following IC and EC transactions are most relevant for configuring the various chips integrated on the FEB2:

- IC or EC write transactions capable of writing from 1 to 4 sequential IpGBT registers
- IC or EC read transactions capable of reading either 1 or 8 sequential IpGBT registers

Configuration of the IpGBTs would be faster with IC or EC transactions capable of writing and reading back 256 sequential IpGBT registers at a time, as this would allow an IpGBT to be configured with a single IC transaction. However, this additional capability would not significantly speed up the overall configuration time of a FEB2 board, since that time is dominated by configuration via I2C of the other devices on the board (including COLUTAv4s, ALFE2s and VTRx+s). The number of IC or EC write and read transactions required to configure each chip type, in either the default or redundant modes, are summarised in the tables below.

In principle the FEB2 slow control can be entirely implemented through IC or EC transactions that write or read only a single IpGBT register. However, this generally more than doubles the total

number of required write transactions, and consequently would increase the time required to initialise the FEB2.

	# of IC/EC Write Transactions to Configure Chip				
Chip, Configuration Mode	1 register	2 register	3 register	4 register	256 register
COLUTAv4, default (EC)	1264	292	0	680	0
COLUTAv4, redundant (IC)	12742	778	1264	3404	0
ALFE2, default (EC)	464	0	0	96	0
ALFE2, redundant (IC)	3040	112	464	688	0
VTRx+, default (EC)	126	0	9	0	0
VTRx+, redundant (IC)	918	36	126	216	0
Control IpGBT, default (IC)	0	0	0	0	1 (optimal)
Control IpGBT, redundant (IC)	1442	103	103	309	0
Data IpGBT, default (EC)	0	0	0	0	1 (optimal)
Data IpGBT, redundant (IC)	1442	103	103	309	0

	# of IC/EC Read Transactions to Configure Chip		
Chip, Configuration Mode	1 register	8 register	256 Register
COLUTAv4, default (EC)	584	98	0
COLUTAv4, redundant (IC)	4857	98	0
ALFE2, default (EC)	112	0	0
ALFE2, redundant (IC)	1182	0	0
VTRx+, default (EC)	63	0	0
VTRx+, redundant (IC)	368	0	0
Control IpGBT, default (IC)	0	0	1 (optimal)
Control IpGBT, redundant (IC)	1060	0	0
Data IpGBT, default (EC)	0	0	1 (optimal)
Data IpGBT, redundant (IC)	625	0	0

## 2. Chips Configured via I2C

COLUTAv4s, ALFE2s and VTRx+s are configured through data IpGBT I2C interfaces. Additionally, data IpGBTs can be configured via a corresponding control IpGBTs I2C interface as a backup to the EC interface. Control IpGBTs operating in redundant mode will also be configured via the other control IpGBT's I2C interface. All chips on the FEB2 use 7-bit I2C addresses, except for the COLUTAv4s which use 10-bit I2C addresses. Additional details on the I2C configuration process for different chip types are described below.

I2C write and read transactions are initiated by a series of IpGBT slow control register writes and reads. This series of IpGBT register writes and reads can be built by combining single or multiple register commands, as has been done in the various development test stands. However, some additional reduction in configuration time might be obtained by implementing in firmware generic I2C read and write processes that will co-ordinate the set of IC or EC transactions required to initiate an I2C transaction.

### 2.1 COLUTAv4 I2C Configuration

The COLUTA configuration data is written through a data IpGBT I2C bus using 10-bit addressing write commands, each containing 8 data bytes. COLUTA configuration bits are divided between global and channel-specific bits, as described in the COLUTAv4 datasheet. For channel-specific

configuration bits, the I2C write command data bytes include two bytes containing subaddressing information and 6 bytes of configuration data. For global configuration bits, each I2C write command includes 8 bytes of configuration data. The lpGBT “I2C\_WRITE\_MULTI\_EXT” command is required to send these multiple bytes of configuration data using 10-bit addressing, instead of the “I2C\_WRITE\_MULTI” command used for other ASICs.

## 2.2 ALFE2 I2C Configuration

ALFE2 configuration data is written through a data lpGBT I2C bus using 7-bit addressing write commands. The ALFE2 has 16 8-bit registers used to store configuration data and which are defined in the ALFE2 datasheet. The registers are configured using I2C write commands in a three-step process, where the 2 LSBs of the ALFE2 7-bit I2C address act as a control register and are modified for each step:

1. Set control register to 0 and send register number via I2C single-byte write command
2. Set control register to 1 and send 0 via I2C single-byte write command
3. Set control register to 2 and register value via I2C single-byte write command

## 2.3 lpGBTv1 I2C Configuration

If the EC interface is not available, then data lpGBTs can be configured via I2C by a control lpGBT following the procedure described in section 3.5.1 of the lpGBT datasheet. The control lpGBT I2C write command process is defined in section 12.3 of the lpGBT datasheet.

## 2.4 Board Monitoring

FEB2 voltage and temperature monitor measurements are performed using the lpGBT v1 built-in ADCs. The operation and read out of these lpGBT ADC measurements is controlled through lpGBT slow control registers writes and reads as described in chapter 13 of the lpGBTv1 manual. These monitoring measurements generally require writing and reading only 1 or 2 lpGBT registers at a time, and so do not introduce any additional IC and EC interface requirements beyond the initialization and configuration of FEB2 chips via I2C. However, implementing the control of the ADC measurement process in firmware might increase the measurement rate and allow more frequent monitoring of the various FEB2 board voltages and temperature.